



Description

JTL60FQC Electrical Converters are the newest addition to the Jetall GPU 400Hz frequency GPU line. The product design allows the unit to either be installed on a caster cart or, trailer mount. With our user-friendly controls and diagnostic system, the converter is easy to use and training is minimal. A state-of-the-art design, ease of use, broad choice of input voltage configurations, customized weather shielding, proven reliability and most competitive pricing are among the many reasons this unit has the versatility to provide power where you need it.

Specifications

Input Power Requirement

- AC current, 3 phase, voltage; 208/230/460/575
- Frequency: 45 to 65 Hz
- Input Power Factor: 0.96
- Input voltage could be strappable in the field

Output Power Performance: 60 KVA

- 115/200 VAC, 3 phase, 400 Hz \pm 0.1%
- Overloads: 100 - 125% – 10 minutes
- 125 - 150%, 30 seconds
- 150 - 200%, 10 seconds
- Load power factor: 0.8 at 100% load

Regulation

- Voltage regulation: < 0.5% for balanced and 30% unbalanced loads
- Phase displacement: 120° \pm 1° for balanced load
120° \pm 2° for 30% unbalanced load
- Voltage modulation: < 1%
- Crest factor: 1.414 \pm 3%
- Transient performance; meets MIL-STD-704F

Protection

- Input; over-/under-voltage overload
- Output; over-/under-voltage
- Over/under frequency transient
- Internal high temperature
- Audible alarm with silencer
- Noise level < 65 DBA at 3 feet

Finish

- Powder coat rather than paint provides superior weather resistance, flexibility and adhesion, plus a strong resistance to chemical agents such as glycol and Skydrol
- Standard color is High Gloss White

Displays - Digital presentation

LCD Display, 4 x 20 characters, backlit panel displaying :

- Operating parameters: ammeter, frequency and voltmeter
- Diagnostics: 16 keypad for menu selections
- Emergency stop: push button type

Optional Equipment

- 28 volt output capability
- Second output capability
- AC Output cable, 9 meter (30 feet), 1 AWG
- DC Output cable, 9 meter (30 feet), 2 AWG
- Custom colors require a paint chip or swatch for accurate color match

